



QuickMount Dual Remote Mount Interface

Turn any Motorola Professional Series CDM 750/ 1250/ 1550 Radio in to a dual mount installation with the QuickMount Interface. All the programmed functions are available from either controlhead including fully independent VOLUME and BACKLIGHTING control.



Each Quick Mount Interface comes with Power Cable and Speaker Pigtail. All Motorola parts including radio, controlheads, data cables and mounting hardware need to be purchased from an authorized Motorola dealer or service shop.

Specifications:

Input Voltage 13.2Vdc (10-16Vdc) negative vehicle ground.

Input Current *Off* less than 2mA, **On/No Audio** less than 300mA.

Full Rated Audio approx. 4.5A with input fuse rating of **5A**.

Rated Audio 3W @ 22 ohms per control head, 13W @ 4 ohms per external speaker connector.

Audio Distortion Less than 4% typical.

Dimensions Length 6-13/64"(158mm), Width 5-3/8"(137mm), Height 1-45/64"(43mm).

Weight 1lb 8oz.(0.75 kilograms).

Operating Temperature -22 to 140 F (-30 to 60 C).

Storage Temperature -67 to 185 F (-55 to 85 C).

IDA Corporation 800-627-4432 / 701-280-1122

sales@idaco.com

www.idaco.com